Specifications

NetBotz Rack Monitor 450 (without 120/240V Power Supply)

NBRK0450
Discontinued on: Jan 8, 2021
() To be end-of-service on: Dec 31, 2024

① To be discontinued

Overview

Presentation	Supports up to 2 external camera pods, 2 sensor pods and up to 18 Universal Sensors.
Lead Time	Usually in Stock

Main

Number Of Rack Unit	1U
Communication Port Protocol	DHCP DNS HTTP HTTPS SMTP SOCKS
Provided Equipment	TCP/IP Country-specific detachable power cord Documentation CD Installation guide Rack mounting brackets Temperature/humidity sensor USB cable

General

Number Of Universal Sensors	2
Supported	

Physical

Height	4.35 cm
Width	43.2 cm
Depth	9.3 cm
Net Weight	1.4 kg
Mounting Location	Front Rear
Mounting Preference	No preference
Mounting Mode	Rack-mounted

Conformance

Standards

FCC part 15 class A ICES-003



Product Certifications

AS/NZS 3548 (C-Tick) class A cUL listed CE GOST IRAM low voltage directive 2006/95/EC NOM UL listed VCCI class A VDE

Environmental

Ambient Air Temperature For Operation	045 °C
Operating Altitude	010000 ft
Relative Humidity	095 %
Ambient Air Temperature For Storage	-1565 °C
Storage Altitude	0.0015240.00 m
Storage Relative Humidity	095 %

Communications & Management

Communication Network Type	RJ45 10/100 Base-T

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	11.4 cm
Package 1 Width	54.6 cm
Package 1 Length	22.9 cm
Package 1 Weight	2.345 kg

Contractual warranty

Warranty

2 years repair or replace

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low- $\rm CO_2$ products.

Learn more about Green Premium >

Well-being performance

Mercury Free	
Rohs Exemption Information	Yes
Eu Rohs Directive	Compliant with Exemptions
Weee	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

