PowerChute™ Network Shutdown v5.0

Operating System, Processor, JRE and Browser Compatibility Chart

by Schneider Electric

OPERATING SYSTEM	LICENSE REQUIRED	VERSION	Edge	Firefox	Chrome
Dell® VxRail **(see Note 3)**	**Yes**	VxRail **7.0.452**, ESXi 7.0.3; 8.0.101, ESXi 8.0.1; **7.0.372**, ESXi 7.0.3, vCenter 7.0.3	✓	✓	✓
		VxRail **4.7.540**, ESXi 6.7.2, vCenter 6.7.2	✓	✓	✓
Nutanix®	**Yes**	AHV - AOS **6.5.3 LTS, 6.5.2 LTS, 6.5.1.6**	✓	✓	✓
		ESXi - AOS **6.5.3.5 LTS, ESXi 7U3C, 7U3M; 6.5.1.6 LTS**, **ESXi 7.0.3; 5.20.4 LTS, ESXi 7.0.3**	✓	✓	✓
Cisco® HyperFlex	**Yes**	Cisco HyperFlex **4.0.2f**, ESXi 7.0.3, 6.7.2	✓	✓	✓
HPE® SimpliVity	**Yes**	HPE SimpliVity Omnistack **4.1.3** (ESXi 7U3F), **4.1.2** (ESXi 7U2a), **4.1.1U1** (ESXi 7U2a), **4.1.0 U1** (ESXi 7.0.3)	✓	✓	✓
VMware® ESXi	Unmanaged Host Shutdown - **No** Managed Host/VM Shutdown - **Yes**	VMware ESXi **8.0 U2, U1d, U1c, U1b, U1a, 8.0b**, **7 Update 3n, 3m, 3i, 6.7.2**	✓	✓	✓
VMware® vSAN	**Yes**	VMware vSAN ESXi **8.0 U1, 7.0.3, 6.7.2**	✓	✓	✓
Microsoft® SCVMM	**Yes**	Windows® Hyper-V Server 2019, SCVMM 2019 (Core)	✓	✓	✓
		Windows® Hyper-V Server 2022, SCVMM 2022 (GUI)	✓	✓	✓
Microsoft® Hyper-V	Unmanaged Host Shutdown - **No** Managed Host/VM Shutdown - **Yes**	Windows® Hyper-V Server Standard 2019	✓	✓	✓
Azure® Stack HCI	**Yes**	Azure® Stack HCI 22H2	✓	✓	✓
Windows® Server 2022	**No**	Windows® Server 2022 Datacenter, Standard	✓	✓	✓
Windows® Server 2019	**No**	Windows® Server 2019 Datacenter	✓	✓	✓
Windows® Server 2016	**No**	Windows® Server 2016 Standard	✓	✓	✓
Windows® 10	**No**	Windows® 10 **21H2, PRO 21H2**	✓	✓	✓
Red Hat® Enterprise Linux®	**No**	Red Hat® Enterprise Linux **9.3**, **9.2, 8.9, 8.8, 8.6**		✓	✓
Ubuntu® Linux®	**No**	Ubuntu® Linux Server **22.04.1 LTS**		✓	✓
SuSE® Linux ®	**No**	SuSE® Linux Enterprise Server **15 SP4**		✓	✓
Debian® Linux®	**No**	Debian® Linux **11.5**		✓	✓
Oracle® Linux®	**No**	Oracle® Linux® **9.3**		✓	✓
CentOS® Linux®	**No**	CentOS® Linux **7.9**		✓	✓

Note 1: Please note APC do not support the free version of VMware ESXi. A VMware license is required. Please refer to Knowledge Base **Answer ID #FA159705** at www.apc.com/support for further information.
Note 2: Supported with latest versions of Chrome, Firefox and Edge
Note 3: Dell VxRail is supported only with Network Management Card 3, with Smart-UPS firmware (SU) v2.2+, Smart-UPS Ultra v2.5+, Symmetra-LX (SY) v2.5+ and Symmetra PX, PX2 v2.4+.
Currently not supported with Easy UPS or Galaxy UPS
Note 4: PowerChute Network Shutdown v5.0 is compatible with AdoptOpenJDK 11-LTS (https://adoptium.net/temurin/releases/?version=11)

© 2024 Schneider Electric, All Rights Reserved. All Trademarks are owned by Schneider Electric, or its affiliated companies in the U.S and other countries.
All other trademarks are property of their respective owners.

Disclaimer: This information is accurate at the point of creation and may be subject to change

Last Updated: 27th March 2024